

CCS-2 30kW

Input Voltage (VAC)

3-Ph 400V (+/- 10%)

Output Voltage (V)

150-1000V DC

Max. Output Power Rating (kW)

30kW DC

Display

7" TFT Color Touch Screen

User Authentication

RFID / Mobile App based

Charger and Vehicle Communication

Power Line Communication (PLC)

Charger Interface

LAN / 4G / WiFi

Place of Installation

Indoor / Outdoor

Ingress Protection

IP54



Applications



HIGHWAY



PARKING



SERVICE STATION



COMMERCIAL



FLEET



RESIDENTIAL



HOTEL



Input Voltage (VAC)	3-Ph 400V (+/-10%)
Efficiency (%)	>94%
Input Frequency (Hz)	50 Hz (+/-1.5 Hz)
Input Current (A AC)	<50 A
Wires	5 wire (L1,L2,L3, N,PE)
	40W
Standby Power	×98
Power Factor	
Current THD	<=5% (50% to 100%) as per IEC 61000-3-12
Number of Outputs	
Output Connector type	IEC 62196-3 (CCS-2)
Output Voltage (V)	150-1000V DC
Max. Output Current (DC)	Max. 100A DC
Max. Output Power Rating (kW)	Max 30 kW DC
Display	7" TFT Color Touch Screen
Electrica metering	To comply with IEC 62052-11 & IC 62053-21
Emergency Push Button	Provided
User Authentication	RFID / Mobile App based
Visual Status Indication	LCD and LED for Mains available, Charging status, System error
Charging Mode	IEC 61851-1 (Mode-4)
Charger and Vehicle Communication	Powe Line Communication (PLC)
Charger and CMS communication	Open Charge Point Protocol 1.6J
Compliance	AIS138 / IS17017-1 / IEC61851-1
Compliance Charger Interface	AIS138 / IS17017-1 / IEC61851-1 LAN / 4G / WiFi
Charger Interface	LAN / 4G / WiFi
Charger Interface Remote Firmware Update	LAN / 4G / WiFi FOTA Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery
Charger Interface Remote Firmware Update Protections	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated
Charger Interface Remote Firmware Update Protections EMI/EMC	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity.
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature	FOTA Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C)
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C)
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-1), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor IP54
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection Enclosure Protection	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor IP54 IK10
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection Enclosure Protection Cooling	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) 495%, non-condensing Indoor / Outdoor IP54 IK10 Forced Air Convection
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection Enclosure Protection Cooling Charging wire length	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor IP54 IK10 Forced Air Convection 5 Mtr
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection Enclosure Protection Cooling Charging wire length Payment systems	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor IP54 IK10 Forced Air Convection 5 Mtr Billing & transaction with various modes of payment
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection Enclosure Protection Cooling Charging wire length Payment systems Memory Storage	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor IP54 IK10 Forced Air Convection 5 Mtr Billing & transaction with various modes of payment To store 50 event logs. To store last 50 charging session information
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection Enclosure Protection Cooling Charging wire length Payment systems Memory Storage Application	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-1), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor IP54 IK10 Forced Air Convection 5 Mtr Billing & transaction with various modes of payment To store 50 event logs. To store last 50 charging session information 4W, Buses
Charger Interface Remote Firmware Update Protections EMI/EMC Ambient Temperature Relative Humidity Place of installation Ingress Protection Enclosure Protection Cooling Charging wire length Payment systems Memory Storage Application Battery back-up	Input Over Voltage, Input Under Voltage, Input Short Circuit, Input over Current, Connection Abnormality, Emergency Stop, Surge Protection upto 4KV, Residual Leakage Current-30mA, Ground Fault, Earth Presence Monitoring, Output Over Current, Over Temperature (Derating/Shutdown), Insulation Resistance Monitoring Reverse Battery Connection Immunity to Electro Static Discharge (IEC 61000-4-2), Voltage Dips and Interruptions (IEC 61000-4-11), Electric Fast Transient (IC 61000-4-4), Voltage Surge (IC 61000-4-5), Radiated Emission, Conducted Emission, Radiated Immunity, Conducted Immunity. -20° to +55° C (derating from +55°C to +65°C) <95%, non-condensing Indoor / Outdoor IP54 IK10 Forced Air Convection 5 Mtr Billing & transaction with various modes of payment To store 50 event logs. To store last 50 charging session information 4W, Buses 15 minutes (Optional)

LUBI EV SOLUTIONS

Lubi Corporate Campus - Near Tragad Under Pass, S.P. Tragad, Ahmedabad - 382421. Gujarat, India Phone: +917961700100 Ext. 323

Sales Enquiries: sales@lubievsolutions.com

www.lubievsolutions.com

Product improvement is a continuous process at 'LUBI'. The data given in this publication is therefore subject to rtevision.